## IN THE CLAIMS

The following listing of claims will replace all prior versions, and listings, of claims in the application.

**Listing of Claims**

1-7.    (Cancelled)

8.    (Previously Presented) A computer-implemented method, comprising:
creating one or more data structures that together store characteristics of a plurality of active branches $B^{active}$ that make up a graph of nodes and branches that form a circuit, wherein $B^{active}$ consists of

a set $B^L$ of zero or more inductive branches, each having a non-zero inductive component but neither a capacitive component nor a variable switch state;

a set $B^C$ of zero or more capacitive branches, each having a non-zero capacitive component but neither an inductive component nor a variable switch state; and

a set $B^A$ of additional branches, each having neither an inductive component, nor a capacitive component;

partitioning $B^{active}$ into a first branch set $B^{active}_{tree}$ and a second branch set $B^{active}_{link}$, where the branches in $B^{active}_{tree}$ form a spanning tree over $B^{active}$, giving priority in said partitioning to branches not in $B^L$ over branches in $B^L$;

Page 2 of 11

sub-partitioning $B_{link}^{active}$ into a third branch set $B_{link}^{L}$ and a fourth branch set $B_{link}^{CA}$,

where $B_{link}^{L} = B_{link}^{active} \cap B^{L}$;

identifying a fifth branch set $B^{CA}$ as the union of

$$B_{link}^{CA},$$

$$B^{C} \cap B_{tree}^{active}, \text{ and}$$

those branches in $B_{tree}^{active}$ that form a closed graph when combined

with $B_{link}^{CA}$;

partitioning $B^{CA}$ into a sixth branch set $\widetilde{B}_{tree}^{CA}$ and a seventh branch set $\widetilde{B}_{link}^{CA}$, where

the branches in $\widetilde{B}_{tree}^{CA}$ form a spanning tree over $B^{CA}$, giving priority in said partitioning to

branches in $B^{C}$ over branches not in $B^{C}$;

identifying an eighth branch set $B_{tree}^{C} = \widetilde{B}_{tree}^{CA} \cap B^{C}$;

selecting a set of state variables comprising:

for each branch of $B_{link}^{L}$, either the inductor current or inductor flux,

and

for each branch of $B_{tree}^{C}$, either the capacitor voltage or capacitor

charge; and

simulating a plurality of states of the circuit using the set of state variables.


9.      (Original) The method of claim 8, wherein said partitioning steps each

comprise an application of a weighted spanning tree algorithm.

10.     (Original) The method of claim 9 wherein, for some positive numbers $w_L$

and $w_C$:

Serial No. 10/043,981
Group Art Unit 2128
Conf. No. 8469

for the partitioning of $B^{active}$, a minimum spanning tree algorithm is used with weight

function $\omega_L(b_j) = \begin{cases} w_L \text{ if branch } b_j \in B^L \\ 0 \text{ otherwise} \end{cases}$ ; and

for the partitioning of $B^{CA}$, a maximum spanning tree algorithm is used with weight

function $\omega_C(b_j) = \begin{cases} w_C \text{ if branch } b_j \in B^C \\ 0 \text{ otherwise} \end{cases}$ .

11-14.  (Cancelled)

15.     (Previously Presented) A system, comprising a processor and a computer-readable medium in communication with said processor, said medium containing programming instructions executable by said processor to:

build state equations for a first topology of an electronic circuit having at least two switching elements, wherein each switching element has a switching state;

solve said state equations at time $t_i$ to provide a state output vector, in which at least two elements control the switching states of the switching elements;

calculate the value of a switching variable as a function of the state output vector, wherein the value reflects whether the switching state of at least one of the switching elements is changing; and

if the value of the switching variable at time $t_i$ indicates that at least one of the switching elements is changing, determine a second topology of the electronic circuit for time $t_i^+$ and obtain state equations for the second topology;

wherein:

said programming instructions comprise a state equation building module, a solver module for ordinary differential equations, and a switching logic module;

Page 4 of 11

Serial No. 10/043,981
Group Art Unit 2128
Conf. No. 8469

said building is performed by the state equation building module;

said solving and calculating are performed by the solver module;

said determining is performed by the switching logic module;

at a time $t_j$, at least two switching elements are each either rising-sensitive or falling-sensitive switches, wherein

rising-sensitive switches change switching state if and only if a controlling element of the state vector has passed from a negative value to a non-negative value; and

falling-sensitive switches change switching state if and only if a controlling element of the state vector has passed from a positive value to a non-positive value; and

the function is the arithmetic maximum of

a maximum of all controlling elements of the state vector that control rising-sensitive switches, and

the negative of the minimum of all controlling elements of the state vector that control falling-sensitive switches.


16.    (Cancelled)


Page 5 of 11